


# MA352 integrated amplifier

- The MA352 Integrated Amplifier is a hybrid design that combines the finest of vacuum tube and solid state audio design principles.
- The result is an eye-catching amplifier that enjoys the best of these two opposing audio philosophies all while reproducing music at the highest quality level.
- Features a vacuum tube preamplifier section that is powered by a pair of 12AX7A and a pair of 12AT7 vacuum tubes.
- Output stage is a direct coupled solid state amplifier that outputs 200 Watts per channel into 8 Ohm speakers or 320 Watts per channel into 4 Ohm speakers.
- Full of numerous McIntosh technologies including Power Guard®, Sentry Monitor™, McIntosh Monogrammed Heatsinks™, 5-Band analog tone control, Home Theater Pass Through, High Drive headphone amplifier with Headphone Crossfeed Director (HXD®), and Power Control.
- Sits atop a beautiful polished stainless steel chassis with a classic McIntosh-styled die cast aluminum name badge attached to each side.



Reproducing Music at the Highest Level

**McIntosh®**

LEGENDARY PERFORMANCE®

[www.mcintoshlabs.com](http://www.mcintoshlabs.com)

# MA352 integrated amplifier

## Preamplifier Stage:

Two 12AX7A and two 12AT7 vacuum tubes

## Output Stage:

Direct-coupled solid-state amplifier

## Power Output:

200 Watts per channel into 8 Ohm speakers or  
320 Watts per channel into 4 Ohm speakers

## Total Harmonic Distortion:

0.03% maximum from 20Hz to 20kHz

## Signal to Noise Ratio (High Level):

93dB

## Tone Controls:

5-Band Analog

## Inputs:

3 Unbalanced  
2 Balanced  
1 Moving Magnet

## Outputs:

2 Subwoofer (mono)

## Headphone Amplifier:

1/4" High Drive with Headphone  
Crossfeed Director (HXD®); powers all  
headphones from 20 to 600 Ohms

## Overall Dimensions (W x H x D):

17-1/2" (44.5cm) x 9-7/8" (25.1 cm)  
x 20-1/2" (52.1cm)

## Weight:

66 lbs (29.9kg) net,  
75 lbs (34.0kg) in shipping carton

## For the Consumer's Protection:

In order to ensure the highest level of customer satisfaction, new McIntosh products may only be purchased from an Authorized McIntosh Dealer; and, with certain limited exceptions may only be purchased over-the-counter or delivered and installed by the Authorized McIntosh Dealer. McIntosh does not warrant, in any way, products that are purchased from anyone who is not an Authorized McIntosh Dealer, or that have had their serial numbers altered or defaced.



## Companion Products

The MT10 or MT5 Precision Turntable, MCD600 SACD/CD Player, MR87 AM/FM Tuner, MS500 Music Streamer, MPC1500 Power Controller, and XR100 Loudspeakers are logical companions for the MA352 Integrated Amplifier. Your Authorized Dealer can provide additional information on other McIntosh product combinations.

To learn more, please call us at 1.800.538.6576.

# McIntosh®

LEGENDARY PERFORMANCE®

[www.mcintoshlabs.com](http://www.mcintoshlabs.com)